

FRAME 40 mid lumen

trim

042-7116137H



Project / Type

Notes

Count / Date



General

Ceiling , Recessed

traffic white , RAL 9016 ¹

1470 lm/m

IP20

4410 lm

LED

4000 K

CRI ≥ 90

L90 / 50000 h

photobio. safety RG 0 - no Risk

initial MacAdam ≤ 3 SDCM

R_g: 99 , R_f: 92 , R₍₁₋₁₅₎: 90

MR 0.81

MDER 0.74

Optical

High Performance Opal

PstLM ≤ 1.0 ²

SVM ≤ 0.4 ²

Electrical

DALI-2

35 W

PC1 220-240V

126 lm/W

12 W/m

Physical

trim

length 3019 mm

width 55 mm

height 60 mm

5.5 kg

Cutout

length 3009 mm

width 45 mm


min. ceiling thickness 8 mm

max. ceiling thickness 25 mm

recessed depth 100 mm

¹ RAL code ² Value of containing product at full load (undimmed)

Light distribution



Product drawing



Installation instructions



Lighting calculator



FRAME 40 mid lumen

trim

042-7116137H



Project / Type

Notes

Count / Date

Maintenance Factors

| Operating Time [h] | 10 000 | 20 000 | 30 000 | 40 000 | 50 000 |
|--------------------|------------------------------|--------|-------------------|---------------------------------|--------|
| LLMF | 0.98 | 0.96 | 0.94 | 0.92 | 0.9 |
| LSF | 1 | 1 | 1 | 1 | 1 |
| MF | LMF × RSMF × LLMF × LSF | | RSMF ^a | Room Surface Maintenance Factor | |
| MF | Maintenance Factor | | LLMF | Lamp Lumens Maintenance Factor | |
| LMF ^a | Luminaire Maintenance Factor | | LSF | Lamp Survival Faktor | |

^a According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

Circuit Breaker Types

| Automatic Circuit Breaker Type | Number of Fixtures |
|--------------------------------|--------------------|
| B10 | 9 |
| B13 | 12 |
| B16 | 15 |
| B20 | 19 |
| C10 | 15 |
| C13 | 20 |
| C16 | 25 |
| C20 | 31 |

Mounting accessories

CONCRETE INSTALLATION HOUSING

| TYPE | L·W·H (MM) | ARTICLE NUMBER(S) |
|---------|------------|-------------------|
| 3038 mm | 3038-57-87 | 042-7195610 |

