

TASK sensor direct / indirect asymmetric power

free standing double
X059-2961078Z



Project / Type

Notes

Count / Date



General

Floor , Standing

black , RAL9005 ¹

IP20

indirect 20600 lm

direct 3810 lm

total 24410 lm

LED

3000 K

CRI ≥ 90

L90 / 50000 h

photobio. safety RG 0 - no Risk

initial MacAdam ≤ 3 SDCM

R_g: 96 , R_r: 90 , R_{t1-15}: 90

MR 0.61

MDER 0.56

Optical

Microprismatic

UGR < 10 , ≥65° <3000 cd/m²

P_{stLM} ≤ 1.0 ²

SVM ≤ 0.4 ²

Electrical

ESSENTIAL sensor (brightness & presence)

195 W

PC1 220-240V

125 lm/W

Physical

U-shape

length 800 mm


width 940 mm

height 2054 mm


12.7 kg

¹ RAL code ² Value of containing product at full load (undimmed)

Light distribution



Product drawing



Installation instructions



TASK sensor direct / indirect asymmetric power

free standing double
X059-2961078Z



Project / Type

Notes

Count / Date

Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.98	0.97	0.95	0.93	0.92
LSF	1	1	1	1	1

MF

LMF × RSMF × LLMF × LSF

MF

Maintenance Factor

LMF^a

Luminaire Maintenance Factor

RSMF^a

Room Surface Maintenance Factor

LLMF

Lamp Lumens Maintenance Factor

LSF

Lamp Survival Faktor

^a According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

Circuit Breaker Types

Automatic Circuit Breaker Type	Number of Fixtures
B10	2
B13	3
B16	4
B20	5
C10	4
C13	5
C16	7
C20	9

