

# SASSO 60 square downlight

semi-recessed  
048-30014111W 002-90771



Project / Type

Notes

Count / Date



**General**  
Ceiling , Semi-Recessed  
black , RAL9005/black <sup>1</sup>  
Inner colour black  
front IP40 , back IP20  
948 lm

**LED**  
2700 K  
CRI ≥ 90  
L80 / 50000 h  
initial MacAdam ≤ 2 SDCM  
R<sub>g</sub>: 99 , R<sub>f</sub>: 91 , R<sub>f(1-15)</sub>: 89  
MR 0.53  
MDER 0.48

**Optical**  
wide flood  
beam angle 51°  
≥65° <1500 cd/m<sup>2</sup>  
PstLM ≤ 1.0 <sup>2</sup>  
SVM ≤ 0.4 <sup>2</sup>


**Electrical**  
non DIM  
12.6 W  
PC2 220-240V  
75 lm/W

**Physical**  
length 72 mm  
width 72 mm  
height 75 mm  
0.06 kg


**Cutout**  
recessed depth 85 mm

<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)

## Light distribution



## Product drawing



## Installation instructions



## Lighting calculator



# SASSO 60 square downlight

semi-recessed  
048-30014111W 002-90771



Project / Type

Notes

Count / Date

## Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.96	0.92	0.88	0.85	0.81
LSF	1	1	1	1	1
MF	LMF × RSMF × LLMF × LSF		RSMF <sup>a</sup>	Room Surface Maintenance Factor	
MF	Maintenance Factor		LLMF	Lamp Lumens Maintenance Factor	
LMF <sup>a</sup>	Luminaire Maintenance Factor		LSF	Lamp Survival Faktor	

<sup>a</sup> According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

## Circuit Breaker Types

Automatic Circuit Breaker Type	Number of Fixtures
B10	43
B13	55
B16	68
B20	85
C10	72
C13	94
C16	116
C20	145

## Components

### CONVERTER

L·W·H (MM)	ARTICLE NUMBER(S)
85-40-22	002-90771



## Optional electrical accessories

### DIN RAIL POWER SUPPLY

L·W·H (MM)	ARTICLE NUMBER(S)
72-90-63	005-6520210



### DIN RAIL LED DRIVER

TYPE	L·W·H (MM)	ARTICLE NUMBER(S)
DALI-2   200-1050 mA   2 x 42W	36-88-59	005-6121030

