

# FRAME 60 mid lumen

trim

052-47L211GZ



Project / Type

Notes

Count / Date



### General

Ceiling | Recessed

grey | RAL 9006 <sup>1</sup>

IP20

665 lm

1160 lm/m

### LED

4000 K

CRI ≥ 90

L90 / 50000 h

initial MacAdam ≤ 3 SDCM

R<sub>g</sub>: 99 | R<sub>f</sub>: 92 | R<sub>i(1-15)</sub>: 90

MR 0.81 | MDER 0.74

### Optical

Microprismatic | microprismatic

PstLM ≤ 1.0 <sup>2</sup> | SVM ≤ 0.4 <sup>2</sup>

### Electrical

non DIM

PC1 | 220-240 V

system 6.9 W

system 96 lm/W <sup>3</sup>

12 W/m

### Physical

trim

length 593 mm | width 77 mm | height 78 mm

1.8 kg

### Cutout


length 583 mm | width 66 mm

min. ceiling thickness 8 mm | max. ceiling thickness 25 mm


recessed depth 104 mm

<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)  
<sup>3</sup> incl. consideration of optical losses, internal control unit losses & operating device efficiency

### Light distribution



### Product drawing



### Installation instructions



### Lighting calculator



# FRAME 60 mid lumen

trim

052-47L211GZ



Project / Type

Notes

Count / Date

## Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.98	0.96	0.94	0.92	0.9
LSF	1	1	1	1	1
MF	LMF × RSMF × LLMF × LSF		RSMF <sup>a</sup>	Room Surface Maintenance Factor	
MF	Maintenance Factor		LLMF	Lamp Lumens Maintenance Factor	
LMF <sup>a</sup>	Luminaire Maintenance Factor		LSF	Lamp Survival Factor	

<sup>a</sup> According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

## Circuit Breaker Types

Automatic Circuit Breaker Type	Number of Fixtures
B10	9
B13	13
B16	15
B20	18
C10	18
C13	26
C16	30
C20	36

## Mounting accessories

### CONCRETE INSTALLATION HOUSING

L·W·H (MM)	ARTICLE NUMBER(S)
635·75·88	035-04066

