

NOBA 40 adjustable

MOVE IT 10

030-6800433



Project / Type _____

Notes _____

Count / Date _____



General

Ceiling / Wall , Track _____

tilt max 90° _____

rotation 365° _____

brushed brass _____

IP20 _____

382 lm _____

optical inset 121 lm/W¹ _____

LED

2700 K _____

CRI ≥ 90 _____

L80 / 50000 h _____

initial MacAdam ≤ 2 SDCM _____

R_g: 99 , R_r: 91 , R_{t(1-15)}: 89 _____

MR 0.53 _____

MDER 0.48 _____

Optical

wide flood _____

beam angle 69° _____

P_{stLM} ≤ 1.0 ² _____

SVM ≤ 0.4 ² _____

Electrical

DALI-2 _____

48 V _____

fixture 3.5 W _____

optical inset 3.2 W _____

PC3 _____

1 DALI Addr. _____

Physical


diameter 40 mm _____

height 40 mm _____

0.22 kg _____

¹ incl. consideration of optical losses
² Value of containing product at full load (undimmed)


Light distribution



wide flood 69°

h (m)	EO° (lx)	ø (m)
1	338	1.37
2	84	2.74
3	38	4.12
4	21	5.49
5	14	6.86

Product drawing



Installation instructions



NOBA 40 adjustable

MOVE IT 10

030-6800433



Project / Type

Notes

Count / Date

Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.96	0.92	0.88	0.85	0.81
LSF	1	1	1	1	1

MF	LMF × RSMF × LLMF × LSF	RSMF ^a	Room Surface Maintenance Factor
MF	Maintenance Factor	LLMF	Lamp Lumens Maintenance Factor
LMF ^a	Luminaire Maintenance Factor	LSF	Lamp Survival Factor

^a According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

