

# TARO 32 downlight

MOVE IT 10 square  
030-6700535F



Project / Type


Notes

Count / Date



Cylindrical spotlight in aluminium; surface anodised gun metal; light inset can be installed and moved without tools by means of clip mount; power supplied via MOVE IT system track profile; hot plug protection; passive cooling of the LEDs through improved heat sink geometry; light colour 3000 K; binning initial MacAdam  $\leq 2$  SDCM; CRI  $\geq 90$ ; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; good glare control through recessed light point level; precise radiation characteristic with 34° beam; no multiple shadows; optical attachment available as accessory; accessories are listed separately; degree of protection IP20; PC3; 48 V; DALI-2 control; flicker-free visual comfort through analogue current control (minimum value 1%); light source replaceable by an authorized professional;


## Light distribution



flood 34°

| h (m) | E0° (lx) | ø (m) |
|-------|----------|-------|
| 1     | 2520     | 0.61  |
| 2     | 630      | 1.21  |
| 3     | 280      | 1.82  |
| 4     | 160      | 2.42  |
| 5     | 100      | 3.03  |

## Product drawing



## General

Ceiling / Wall | Track

gun metal

IP20

774 lm

## LED

3000 K

CRI  $\geq 90$

L80 / 50000 h

initial MacAdam  $\leq 2$  SDCM

R<sub>g</sub>: 100 | R<sub>f</sub>: 91 | R<sub>{1-15}</sub>: 89

MR 0.59 | MDER 0.53

## Optical

flood | beam angle 34°

PstLM  $\leq 1.0$ <sup>1 2 3 4</sup> | SVM  $\leq 0.4$ <sup>1 2 3 4</sup>

## Electrical

DALI-2 | 1 DALI Addr.

PC3 | 48 V

fixture 9.6 W

fixture 81 lm/W<sup>5</sup>

## Physical

diameter 32 mm | height 60 mm

0.06 kg

<sup>1</sup> soft lens BO 32 007-1965960 <sup>2</sup> oval lens BO 32 007-1965860  
<sup>3</sup> wallwasher lens BO 32 007-1965760  
<sup>4</sup> Value of containing product at full load (undimmed)  
<sup>5</sup> incl. consideration of optical losses, internal control unit losses & operating device efficiency

## Installation instructions

