

SASSO 100 round adjustable trim soft acoustic ceiling

048-2720914W 048-2796398 002-90789



Project / Type _____
 Notes _____
 Count / Date _____



General

Ceiling | Recessed
 tilt max 30°
 rotation 360°
 matt silver
 Mounting set jet black
 front IP40 | back IP20
 2470 lm
 fixture 109 lm/W ¹

LED

2700 K
 CRI ≥ 90
 L80 / 50000 h
 initial MacAdam ≤ 2 SDCM
 R_g: 97 | R_f: 91 | R_{f(1-15)}: 87
 MR 0.52 | MDER 0.47

Optical

wide flood | beam angle 56°
 ≥65° <1500 cd/m²
 PstLM ≤ 1.0 ² | SVM ≤ 0.4 ²

Electrical

DALI-2 | 1 DALI Addr.
 PC2 | 220-240 V
 system 26.7 W | fixture 22.7 W
 36 Vf | 650 mA

Physical

with trim for acoustic ceiling
 diameter 114 mm | height 95 mm
 0.7 kg


Cutout

diameter 100 mm
 min. ceiling thickness 25 mm | max. ceiling thickness 40 mm
 recessed depth 100 mm


¹ incl. consideration of optical losses & internal control unit losses
² Value of containing product at full load (undimmed)

Round recessed spotlight in die-cast aluminium; 1 lamp; surface matt silver; 360° rotatable and 30° tiltable; installation without tools in mounting set due to patented ball catch system; round installation housing; with trim jet black; for installation in soft acoustic ceilings; suitable for ceiling thickness of 25-40 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 56° beam; degree of protection from below IP40 (from above IP20); PC2; 220-240 V; incl. DALI-2 converter; through wiring connection box, 3-pole or 5-pole, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



Installation instructions



Lighting calculator

