

# CONVERTER


007-1952580



Project / Type

Notes

Count / Date



Electrical

PC2

38 W

Dim DALI, Dim Dali 2

min 198 V

max 264 V

$\eta$  90 %

Constant Current

min 50 Hz

max 60 Hz

constant current 500 mA

Physical

length 147 mm | width 44 mm | height 30 mm



# CONVERTER

007-1952580



Project / Type

Notes

Count / Date

## Circuit Breaker Types

Automatic Circuit Breaker Type	Number of Converters
B10	31
B13	40
B16	50
B20	62
B25	78
C10	52
C13	67
C16	85
C20	104
C25	130

