

# POWER SUPPLY

002-90726



Proyecto / Tipo \_\_\_\_\_

Notas \_\_\_\_\_

Cantidad / Fecha \_\_\_\_\_



## Eléctrico

600 mA \_\_\_\_\_

CP1 \_\_\_\_\_

30 W \_\_\_\_\_

non DIM \_\_\_\_\_

198 V \_\_\_\_\_

264 V \_\_\_\_\_

$\eta$  89 % \_\_\_\_\_

Corriente Constante \_\_\_\_\_

50 Hz \_\_\_\_\_

60 Hz \_\_\_\_\_

## Físico

longitud 210 mm \_\_\_\_\_

ancho 30 mm \_\_\_\_\_

altura 21 mm \_\_\_\_\_





Proyecto / Tipo \_\_\_\_\_

Notas \_\_\_\_\_

Cantidad / Fecha \_\_\_\_\_

## Tipos de disyuntores

Tipo de disyuntor automático	Número de convertidores
B10	31
B13	40
B16	50
B20	62
B25	78
C10	52
C13	67
C16	85
C20	104
C25	130