

# CONVERTER

002-90776



Projet / Type \_\_\_\_\_

Notes \_\_\_\_\_

Quantité / Date \_\_\_\_\_



**Général**

38 W \_\_\_\_\_

**Electrique**

700 mA \_\_\_\_\_

CP2 \_\_\_\_\_

38 W \_\_\_\_\_

Dim DALI, Dim Dali 2 \_\_\_\_\_

min 198 V \_\_\_\_\_

max 264 V \_\_\_\_\_

$\eta$  90 % \_\_\_\_\_

Courant Constant \_\_\_\_\_

min 50 Hz \_\_\_\_\_

max 60 Hz \_\_\_\_\_

courant constant 700 mA \_\_\_\_\_

**Physique**

longueur 147 mm \_\_\_\_\_

largeur 44 mm \_\_\_\_\_

hauteur 30 mm \_\_\_\_\_



# CONVERTER

002-90776



Projet / Type

Notes

Quantité / Date

## Types de disjoncteurs

Type de disjoncteur automatique	Nombre de convertisseurs
B10	31
B13	40
B16	50
B20	62
B25	78
C10	52
C13	67
C16	85
C20	104
C25	130

