

# SASSO 100 round adjustable


trim 2 lamps

048-2720617F 048-2798317 002-90779




Round recessed spotlight in die-cast aluminium; 2 lamps; surface white; 360° rotatable and 30° tiltable; installation without tools in mounting set due to patented ball catch system; oval installation housing; with trim traffic white; suitable for ceiling thickness of 2-25 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 4000 K; binning initial MacAdam  $\leq 2$  SDCM; CRI  $\geq 90$ ; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 45° beam; UGR  $\leq 19$ ; degree of protection from below IP40 (from above IP20); PC2 220-240V; incl. DALI-2 converter; through wiring connection box, 3-pole or 5-pole, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

## Light distribution



## Product drawing



Project / Type	
Notes	
Count / Date	



## General

Ceiling , Recessed	
tilt max 30°	
rotation 360°	
white , RAL9016 <sup>1</sup>	
Mounting set traffic white	
front IP40 , back IP20	
3500 lm	

## LED

4000 K	
CRI $\geq 90$	
L80 / 50000 h	
initial MacAdam $\leq 2$ SDCM	
R <sub>g</sub> : 97 , R <sub>r</sub> : 90 , R <sub>(1-5)</sub> : 89	
MR 0.81	
MDER 0.74	

## Optical

flood	
beam angle 45°	
UGR $< 19$	
PstLM $\leq 1.0$ <sup>2</sup>	
SVM $\leq 0.4$ <sup>2</sup>	

## Electrical

DALI-2	
40 W	
total insets 34 W	
PC2 220-240V	
88 lm/W	
1 DALI Addr.	

## Physical

trim	
length 218 mm	
width 118 mm	
height 95 mm	
0.61 kg	

## Cutout

diameter 105 mm	
length 205 mm	
min. ceiling thickness 2 mm	
max. ceiling thickness 25 mm	
recessed depth 100 mm	

<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)

## Installation instructions



## Lighting calculator

