

LINEA inner corner opal / opal  
wall system  
058-6111D37AH



Project / Type \_\_\_\_\_


Notes \_\_\_\_\_

Count / Date \_\_\_\_\_




Light fitting and front cover made of extruded aluminium profile; angular design; 90° corner element - inner corner; for lighting systems; no visible screws; surface white powder coated; suitable for wall mounting; homogeneous wall or ceiling illumination through uniform direct/indirect light distribution; direct and indirect light component: HPO (High Performance Opal) cover for uniform illumination; light colour: tunable white diodes (2700-5000 K); binning initial MacAdam  $\leq 3$  SDCM; CRI  $\geq 90$ ; min. 85% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; degree of protection IP20; PC1 220-240V; photobiological safety according to IEC 62471 risk group RG 0 - no Risk; incl. DALI-2 converter; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



General

Ceiling , Suspended \_\_\_\_\_

white , RAL9010 <sup>1</sup> \_\_\_\_\_

3330 lm/m \_\_\_\_\_

IP20 \_\_\_\_\_

indirect 2020 lm \_\_\_\_\_

direct 2020 lm \_\_\_\_\_

total 4040 lm \_\_\_\_\_

LED

tunable white \_\_\_\_\_

2700 K - 5000 K \_\_\_\_\_

CRI  $\geq 90$  \_\_\_\_\_

L85 / 50000 h \_\_\_\_\_

photobio. safety RG 0 - no Risk \_\_\_\_\_

initial MacAdam  $\leq 3$  SDCM \_\_\_\_\_

R<sub>g</sub>: 99 , R<sub>f</sub>: 90 , R<sub>(1-15)</sub>: 88 \_\_\_\_\_

MR 0.53 \_\_\_\_\_

MDER 0.48 \_\_\_\_\_

Optical

High Performance Opal \_\_\_\_\_

PstLM  $\leq 1.0$  <sup>2</sup> \_\_\_\_\_

SVM  $\leq 0.4$  <sup>2</sup> \_\_\_\_\_

Electrical

DALI-2 \_\_\_\_\_

42 W \_\_\_\_\_

PC1 220-240V \_\_\_\_\_

96 lm/W \_\_\_\_\_

34 W/m \_\_\_\_\_

Physical

length 633 mm \_\_\_\_\_

width 633 mm \_\_\_\_\_

height 100 mm \_\_\_\_\_

<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)

Installation instructions



Lighting calculator

