

# NOBA 60 adjustable

MOVE IT 10

030-6820633



Project / Type

Notes

Count / Date



### General

Ceiling / Wall , Track

tilt max 90°

rotation 365°

brushed brass

IP20

955 lm

### LED

4000 K

CRI ≥ 90

L80 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 97 , R<sub>f</sub>: 90 , R<sub>(1-15)</sub>: 89

MR 0.81

MDER 0.74

### Optical

Wide Flood

beam angle 67°

### Electrical

DALI-2

8.1 W

PC3

118 lm/W


1 DALI Addr.

### Physical

diameter 60 mm

height 60 mm


### Light distribution



wide flood 67°

h (m)	EO° (lx)	ø (m)
1	908	1.31
2	227	2.63
3	101	3.94
4	57	5.26
5	36	6.57

### Product drawing



### Installation instructions



# NOBA 60 adjustable

MOVE IT 10

030-6820633



Project / Type

Notes

Count / Date

## Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.96	0.92	0.88	0.85	0.81
LSF	1	1	1	1	1

MF	LMF × RSMF × LLMF × LSF	RSMF <sup>a</sup>	Room Surface Maintenance Factor
MF	Maintenance Factor	LLMF	Lamp Lumens Maintenance Factor
LMF <sup>a</sup>	Luminaire Maintenance Factor	LSF	Lamp Survival Faktor

<sup>a</sup> According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

