

# NOBA 40 adjustable

MOVE IT 10

030-6800533



Project / Type

Notes

Count / Date



### General

Ceiling / Wall , Track

tilt max 90°

rotation 365°

brushed brass

IP20

428 lm

### LED

3000 K

CRI ≥ 90

L80 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 100 , R<sub>f</sub>: 91 , R<sub>f1-15</sub>: 88

MR 0.59

MDER 0.53

### Optical

Wide Flood

beam angle 67°

### Electrical

DALI-2

3.5 W

PC3

122 lm/W


1 DALI Addr.

### Physical

diameter 40 mm

height 40 mm


### Light distribution



wide flood 67°

h (m)	EO° (lx)	ø (m)
1	407	1.31
2	102	2.63
3	45	3.94
4	25	5.26
5	16	6.57

### Product drawing



### Installation instructions



# NOBA 40 adjustable

MOVE IT 10

030-6800533



Project / Type

Notes

Count / Date

## Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.96	0.92	0.88	0.85	0.81
LSF	1	1	1	1	1

MF

MF

LMF<sup>a</sup>

$LMF \times RSMF \times LLMF \times LSF$

Maintenance Factor

Luminaire Maintenance Factor

RSMF<sup>a</sup>

LLMF

LSF

Room Surface Maintenance Factor

Lamp Lumens Maintenance Factor

Lamp Survival Faktor

<sup>a</sup> According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

