

# SASSO 100 square wallwasher/floor

trim 2 lamps

048-2750911W 048-279931G 002-90767




Project / Type	
Notes	
Count / Date	



Recessed square spotlight in die-cast aluminium; 2 lamps; surface black; installation without tools in mounting set due to patented ball catch system; rectangular installation housing; with trim white aluminium; suitable for ceiling thickness of 2-25 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam  $\leq 2$  SDCM; CRI  $\geq 90$ ; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; with specially computed, asymmetrical reflector for homogeneous lighting intensity; high quality reflector with micro-faceted, aluminum-vaporised surface; PC2; 220-240 V; incl. DALI-2 converter; through wiring connection box, 3-pole or 5-pole, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

## Light distribution



## Product drawing



## General

Ceiling , Recessed	
black , RAL 9005 <sup>1</sup>	
Mounting set white aluminium	
IP20	
3740 lm	
fixture 128 lm/W <sup>2</sup>	

## LED

2700 K	
CRI $\geq 90$	
L80 / 50000 h	
initial MacAdam $\leq 2$ SDCM	
R <sub>g</sub> : 97 , R <sub>f</sub> : 91 , R <sub>(1-15)</sub> : 87	
MR 0.52	
MDER 0.47	

## Optical

wallwasher floor	
PstLM $\leq 1.0$ <sup>3</sup>	
SVM $\leq 0.4$ <sup>3</sup>	

## Electrical

DALI-2	
220-240 V	
system 34 W	
fixture 14.6 W	
36 Vf	
450 mA	
fixture 29.2 W	
PC2	

## Physical

trim	
length 218 mm	
width 118 mm	
height 96 mm	
0.78 kg	

## Cutout

length 210 mm	
width 112 mm	
min. ceiling thickness 2 mm	
max. ceiling thickness 25 mm	
recessed depth 100 mm	

<sup>1</sup> RAL code  
<sup>2</sup> incl. consideration of optical losses & internal control unit losses  
<sup>3</sup> Value of containing product at full load (undimmed)

## Installation instructions



## Lighting calculator

